

## **AMENDMENTS TO THE CLAIMS:**

### **Complete Listing of Claims**

- 1     1. (currently amended)    A comparator with hysteresis comprising a first  
2     transistor (M1) whose gate forms the one input of the comparator and a second  
3     transistor (M2) whose gate forms the other input of the comparator, the main  
4     current paths of both transistors (M1, M2) being connected to each other at one  
5     end, characterized by a third transistor (M3) and a fourth transistor (M4) being  
6     provided, the gate of said third transistor (M3) being connected to the gate of  
7     said first transistor (M1) and the ~~its~~ main current path of said first transistor being  
8     connected ~~circuit~~ between the one end of the main current paths of said first  
9     and second transistor (M1, M2) and connected via the main current path of said  
10    fourth transistor (M4) to the other end of said main current path of said second  
11    transistor (M2), and the gate of said fourth transistor being connected to the  
12    output signal or inverted output signal of said comparator.
  
- 1     2. (original) The comparator as set forth in claim 1 wherein said transistors (M1,  
2     M2, M3, M4) are bipolar transistors.
  
- 1     3. (original) The comparator as set forth in claim 1 wherein said transistors (M1,  
2     M2, M3, M4) are MOS-FETs.
  
- 1     4. (original) The comparator as set forth in claim 3 wherein the width/length  
2     ratio of said first transistor (M1) is larger than the width/length ratio of said third  
3     transistor (M3).

1 5. (currently amended) The comparator as set forth in claim 1 comprising, in  
2 addition, a fifth transistor (M11) and a sixth transistor (M12), the gate of said fifth  
3 transistor (M11) being connected to the gate of said second transistor (M2) and  
4 ~~the its~~ main current path being connected ~~circuit~~ed between the one end of the  
5 main current ~~paths~~ path of said first and said second transistor (M1, M2) and via  
6 the main current path of said sixth transistor (M12), ~~to~~ the other end of the main  
7 current path of said first transistor (M1), and the gate of said sixth transistor  
8 (M12) being connected to the output signal of said comparator when the gate of  
9 said fourth transistor (M4) is connected to the inverted output signal of said  
10 comparator, and the gate of said sixth transistor (M12) being connected to the  
11 inverted output signal of said comparator, when the gate of said fourth transistor  
12 (M4) is connected to the output signal of said comparator.

1 6. (currently amended) The comparator as set forth in claim 4 comprising, in  
2 addition, a fifth transistor (M11) and a sixth transistor (M12), the gate of said fifth  
3 transistor (M11) being connected to the gate of said second transistor (M2) and  
4 ~~the its~~ main current path being connected ~~circuit~~ed between the one end of the  
5 main current ~~paths~~ path of said first and said second transistor (M1, M2) and via  
6 the main current path of said sixth transistor (M12), ~~to~~ the other end of the main  
7 current path of said first transistor (M1), and the gate of said sixth transistor  
8 (M12) being connected to the output signal of said comparator when the gate of  
9 said fourth transistor (M4) is connected to the inverted output signal of said  
10 comparator, and the gate of said sixth transistor (M12) being connected to the  
11 inverted output signal of said comparator, when the gate of said fourth transistor  
12 (M4) is connected to the output signal of said comparator.

1 7. (original) The comparator as set forth in claim 5 wherein, in addition, a sub-  
2 circuit is provided which ensures that said status of the output signal of said  
3 comparator is locked even when the voltage level at the one and/or other input of  
4 said comparator disappears.

1 8. (currently amended) The comparator as set forth in claim 5 wherein the  
2 one end of said main current ~~paths~~ path of said first transistor and of said  
3 second transistor is connected to a current source.

1 9. (currently amended) The comparator as set forth in claim 5 wherein the  
2 one end of said main current path of said first transistor and the main current  
3 path of said second transistor is connected in each case via the main current  
4 path of the other ~~transistors~~ transistor to a supply voltage.

1 10. (currently amended) An ASK demodulator comprising a comparator with  
2 hysteresis, comprising:

3 a first transistor (M1) whose gate forms the one input of the comparator  
4 and a second transistor (M2) whose gate forms the other input of the  
5 comparator, the main current paths of both transistors (M1, M2) being connected  
6 to each other at one end, characterized by a third transistor (M3) and a fourth  
7 transistor (M4) being provided, the gate of said third transistor (M3) being  
8 connected to the gate of said first transistor (M1) and ~~the its~~ main current path of  
9 said first transistor being connected ~~circuit~~ed between the one end of the main  
10 current paths of said first and second transistor (M1, M2) and connected via the  
11 main current path of said fourth transistor (M4) to the other end of said main  
12 current path of said second transistor (M2), and the gate of said fourth transistor  
13 being connected to the output signal or inverted output signal of said  
14 comparator.

1 11. (currently amended) The ASK demodulator as set forth in claim 10 further  
2 comprising, a rectifier (2, C1) whose output (5) is connected to a first voltage  
3 follower (6) whose output is connected to a first capacitor (C2) and the output of  
4 the rectifier is connected to a second voltage follower (7) whose output is  
5 connected to a second capacitor (C3) ~~(C2)~~, the capacitance of which is smaller  
6 than the capacitance of said first capacitor (C2), said first capacitor (C2) being  
7 connected to the one input and said second capacitor (C3) being connected to  
8 the other input of said comparator (8).

1 12. (original) The ASK demodulator as set forth in claim 11 wherein said two  
2 voltage followers (6, 7) each comprise opposing offset voltages.

1 13. (original) The ASK demodulator as set forth in claim 12 wherein said  
2 comparator (8) comprises an offset voltage.